

Piezo Siren

Piezo siren



LD-80

Operating voltage: 7~14VDC
Current consumption: 130mA
Operating frequency: 1.5~3.5KHz
Alarm output: 110dB
Reverse polarity protection
Size(mm): 60Ø, Base 75x18
Weight: 60g



LK-97

Operating voltage: 10~16V(DC12V model)
18~28V(DC24V model)
Current consumption: 120mA(DC12V model)
80mA(DC24V model)
Operating frequency: 2.4~3.7KHz
Alarm output: 110dB
Reverse polarity protection
Size(mm): 122Lx73Wx43H
Weight: 132g



LD-98 (Flush mount siren)

Operating voltage: 7~14VDC
Current consumption: 150mA
Operating frequency: 2.4~3.7KHz
Alarm output: 110dB
Reverse polarity protection
Size(mm): 126Lx76Wx40H
Weight: 110g

Piezo siren with strobe



LD-87 (Ceiling-mount)

Operating voltage: 10~14VDC
Current consumption: 250mA
Operating frequency: 2.4~3.7KHz
Alarm output: 122dB
Reverse polarity protection
Size(mm): 110Øx46
Weight: 160g



LK-95 (Siren & strobe, strobe only)

LK-96 (Siren & strobe)

LK-96L (Siren & strobe, LED indicator)


LK-96T (Siren & strobe, tamper SW.)

Operating voltage: 10~16V(DC12V model)
18~28V(DC24V model)
Current consumption: 150mA(DC12V model)
100mA(DC24V model)
Operating frequency: 2.4~3.7KHz
Alarm output: 110dB
Strobe: 8 pcs super bright LED strobe
Tamper switch: Contact rating 0.5A/30VDC(LK-96T)
Reverse polarity protection
Size(mm): 122Lx73Wx43H
Weight: 140g




Tamper Switch


LK-95




LK-96



LK-96L



LK-96T



Intruder alarm with strobe



LD-281 (Negative activated)

LD-282 (Positive activated)

LD-283 (W/Back-up battery positive activated)

LD-285 (W/Back-up battery negative activated)

Specification:

- ◆ Operating voltage: 11V~14V DC (12V Nominal)
- ◆ Power consumption: Siren: 200mA
Strobe: 250mA
- ◆ Siren output: 115 decibel
- ◆ Strobe luminous flux: 25lm
- ◆ Size(mm): 241(L)x160(W)x51(H)

Features:

- ◆ Built-in Anti-tamper switch/with Feed-back Terminal
- ◆ Weatherproof, UV proof, Hi-impact. (3mm Polycarbonate housing)
- ◆ Six strobe lights polarity reverse protection
- ◆ Cable-cutting/Movement Activated(LD-283/LD-285)
- ◆ Circuit for AUTO-RECHARGING battery(LD-283/LD-285)