

Garrison

LK-1010-1 LK-1010-2

DIGITAL KEYPAD



FEATURES

- Programmable code number in 1 to 14 figures.
- Code number easily changeable and EEPROM keeps memorized codes permanently even if power supply failed.
- Option of one channel (LK-1010-1) or two channels (LK-1010-2).
- Two kinds/levels of code numbers available at the same time (LK-1010-2).
- Emits electronic beeping every time key-button is depressed.
- Output indication by beeping and by LED lamp.
- With keypad back-lit. • Tamper switch provided.
- With doorbell push button. • Easy to install.
- Most suited for remote control of security system, unlocking electric lock or electric shutter, etc.

SPECIFICATIONS

Code Number: In 1 to 14 figures.

Power Supply: 10.5-16V DC.

Power Consumption: (LK-1010-1)

Quiescent - 30mA	(LK-1010-2)
Relay on - 60mA	Quiescent - 60mA
	Both relay on 115mA

Output: Relay contact NO/NC (1A/24V DC or 0.5/120V AC)

Selectable alternate or momentary operation.
Momentary operate time 1 to 255 seconds programmable

Tamper Switch: Provided.

Doorbell Switch: 0.5A/120VAC

Operation Temperature: -10°C~55°C.

Wiring: Lead wiring (lead length: 22cm)

Housing: Molded ABS resin.

Dimensions: 130L x 80W x 34H mm